
## Cern LHC Interactive Tunnel Installation manual

Version 4 Tv August 2018

Denarié Charles-Henri Cern Travelling Exhibition Manager Tel: 0041 75 411 0704 Email: charles-henri.denarie@cern.ch



## Mounting sequence

- Installation of the lino floor
- Truss structure mounting
- Screen support horizontal bars
- Screen support vertical bars
- Black top cover installation
- Screen installation
- Video projectors installation
- Kinect installation
- Pc and sound system installation
- Cabling Power, Video , sound, Kinect, Small router
- Test
- Vertical black covers installation
- Test

## Lino installation

- Lino is foreseen to be Below the 4 feet of the structure.
- Please keep 1.5m from lino to room wall for access on the back part.
- If possible use double side tape to fixe it on the floor


#### Truss structure mounting

- On the trolleys you have:
- 4 feet, 2 piece 2 m long and 4 pieces with 1.5m attaches to an angle.
- On the large box -03 you will find the pines and clamps for the assembly
- First mount the top part of the structure on the floor and then the feet will be add.
- Please identify the pieces to be fixed together with the stickers like on the picture below
- For example Truss 1 to Truss 1.




- The part with the screens wall is the one with stickers Truss 1 and Truss 2.
- When the top rectangle is done and secure by pines and clamps, you have to add the feet, for this lift one side (2 persons) and a 3rd on will place the feet on this side.
- Please secure directly with the pin and the clamp the fixation.
- Than lift the other side and add the 2 others feet.
- Adjust the position of the structure on the lino.

#### Truss junctions

















#### Screens structure mounting


Horizontals bars should be assemble as on the picture








• Horizontal bars will be then fixe on the structure on the accoding position on the feet




#### Screen support vertical bars installation





## Top cover installation

- The black top cover is fixed directly on the truss structure Please put the cover slightly above the screen to avoid external light
- (max 5 cm, to allow top ventilation )



#### **Screen Installation**

- The screens are inside the boxes -00 and -01.
- This type of screen with very narrow bezel is VERY FRAGILE.
- You should NEVER put them on floor, or let them laying on back side or front side.
- You have to take them from the boxes and **install them directly**.
- They are mark from 1 to 4



- In box -00 you have Screen 1 and 2
- In box -01 you have Screen 3 and 4
- Please install first the screen 1 and align it to the mark on the truss





Engage first the top part of the support





Then pulling the small cable engage the bottom part



#### Secure Screens on position








#### Installation of the video projectors









Kinect installation on right and left near the screen





#### Pc and sound system


- Pc and sound system, router,
- have now to be install on the floor, below the screens



# Cabling


- Power cables
- Video cables
- Sound

# Power have to be distributed on the 3 phases

















Forex panels black cover installation



		Forex	<pre>c Installation</pre>				
Left Side		Front view					Right side
			Forex 1	Fore	< 2		
Forex 9	Forex 3	3				Forex 7	Forex 11
	Forex 4		Screen Wall				
Forex 10						Forex 8	Forex 12
		Forex 5		Forex 6			
			Rear View				
	Fo	orex 13	Forex 14	Forex 15	Forex 16	5	
	F	orex 17	Forex 18	Forex 19	Forex 20		
		STEX 17	TOTEX 18	10167 13	TOTEX 20		







#### Install CERN Forex Logo



